HTRACK CURRENT LIMITER

WAC LIGHTING

120V Track System

Responsible Lighting®

Low Cost Energy Code Compliance Made Easy

- Easy to install and assures compliance to California Title 24 or ASHRAE 90.1 requirements
- Energy code track installations are subject to wattage limitations based upon the size and usage of the space
- To order appropriate current limiter, select the model number which corresponds to the H system to the maximum allowable wattage
- If the track is overloaded the current limiter circuit breaker will trip and shut down power to the track.
- May be reset when the overall sum of fixture wattages are reduced below the circuit breaker rating

Fixture Type:				
Catalog Number:				
Project:				

Location:

breaker rating		Location:						
		Model		Circuit Breaker	Max Wattage	Finis	n	
Slim Single Live End	51/8" 11/8" 11/8" 11/8"	THL-HLES	1/5A	200mA	24W			
Single Live End	5½" 65%"	THL-HLE	1/2A 1A 2A 5A 7A THL-HLE	1A 2.5A 5A 7.5A	60W 120W 300W 600W 900W 1200W			
Double Live End	5%" 	THL-HI	1-1/5A 2-1/5A	200mA 200mA per end	24W 24W per end	BK BN DB	Black Brushed Nickel Dark Bronze	
Double Live End (Left)	1½" 5½" 65%"	THL-LEFT	1-1/2A 2-1/2A 1-1A 2-1A 1-2A 2-2A 1-5A 2-5A	500mA 500mA per end 1A 1A per end 2.5A 2.5A per end 5A 5A per end 7.5A	60W 60W per end 120W 120W per end 300W 300W per end 600W 600W per end	WT	White	
Double Live End (Right)	5 %"	THL-RIGHT	1-7A 2-7A 1-10A 2-10A	7.5A 7.5A per end 10A 10A per end	900W 900W per end 1200W 1200W per end			

Example: THL-LEFT-1-1/5A-WT

WAC Lighting www.waclighting.com Phone (800) 526.2588 • Fax (800) 526.2585 Headquarters/Eastern Distribution Center 44 Harbor Park Drive • Port Washington, NY 11050 Phone (516) 515.5000 • Fax (516) 515.5050 Western Distribution Center 1750 Archibald Avenue • Ontario, CA 91760 Phone (800) 526.2588 • Fax (800) 526.2585